









Mounting instruction

AIRCELL®5

BNC-One-hole Socket, crimp/solder / Art. No. 7727

 <p>1. Cut off cable tail right-angled. Move the crimp sleeve over the cable tail.</p>	 <p>5. Remove 4mm of the foamed dielectric.</p>
 <p>2. Remove 17mm of the outer sheathing with a knife.</p>	 <p>6. Put the inner pin onto the inner conductor and solder it.</p>
 <p>3. Bend copper braid upwards right-angled.</p>	 <p>7. Insert the so prepared cable end into the connector housing as far it goes (click). Cut off the copper braid and move the crimp sleeve forward..</p>
 <p>4. Remove 5mm of the copper foil with a knife.</p>	 <p>8. Crimp the crimp sleeve with a crimp tool; herewith the copper braid will be clamped between the socket housing and the crimp sleeve.</p>

Maahantuonti ja myynti:

PARATRONIC OY

Heikkiläntie 26, 63130 MÄYRY

Puh 0400 297526 paratronic@paratronic.fi

paratronic.fi

SSB- Electronic GmbH *Ostenfeldmark 21* 59557 Lippstadt

www.ssb-electronic.de

20-Feb-14